


Go to VARIAC.com to purchase and for technical support. Made in the USA

.88 [22.2] DIA. KNOCKOUT -6 PLACES — THIS SIDE TERMINAL COVER -3 PLACES ⊖

.38 [9.5] DIA. SHAFT -


2.62 [66.7] DIA. KNOB

UNIT IS SUPPLIED WITH A 3.50 [95.2] DIA. 0-100 GRADUATED DIAL PLATE FOR PANEL MOUNTING.



SCHEMATIC
THREE PHASE WYE
FUSFS RFCOMMENDED BUT NOT SUPPLIED

				FUSES	S RECOM	MENDE	D BUI	NOT SUPP	LLED			
					SPECIF	FICATION	IS					
	INPUT		OUTPUT					SHAFT	TERMINAL CONNECTIONS			
WIRING	VOLTS	HERTZ	VOLTS	CUR	CONSTANT CURRENT LOAD		STANT DANCE AD	ROTATION TO INCREASE	FOR INCREASING VOLTAGE AS VIEWED FROM BASE END			
				MAX. AMPS	MAX. KVA	MAX. AMPS	MAX. KVA	10202		INPUT		OUTPUT
THREE PHASE WYE TT	240	50/60	0 040			20	8.30	CW	2-2-2		4-4-4	3-3-3
			0-240	15	6.22			CCW	4-4-4		2-2-2	3-3-3
		60	0-280	15	7.26			CW	1-1-1		4-4-4	3-3-3
				15				CCW	5-5-5		2-2-2	3-3-3
UNLESS OTHERWISE SPECIFIED. TOLERANCE IS ± DECIMALS HOLES ANGLES DRAFT .XX 00000: .00 10000: .01 1° 1-1/2° IN [mm] .XXX .005					SPEC	C. CC			DL DRAWING NSFORMER			
MATERIAL: ALL DIMENSIONS APPLY AFTER PLATING				TER		10DEI		510CT-	T 7 A COM		ENERGY PRODUCTS CO. OMENTS CORPORATION OF AMERICA COMPANY AYTON, OHIO U.S.A.	
The information and design disclosed herein was originated by and is the property of STACO ENERGY PRODUCTS CO., which reserves all potent, proprietary, design, manufacturing, reproduction, use and sale rights thereto, and to any article disclosed therein except to the extent rights are expressly granted to others. The foregoing does not apply to vendor proprietary parts.							/2001	FIRST USED ON 1510CT-3	DO NOT SCALE DWG.	CUSTOMER APPROVAL DATE DWG. DWG. NO.		DATE
						DATE		WEIGHT APPROX. 55.50 LBS	83008			7075
					EER	DATE		.50=1	SHEET 1 OF 1	D	031-3	20/5



→ 6.25 [158.8] **→**

—— 7.25 [184.2] ——

16.09 [408.6]

14.96 [380.0]

8.02 [203.6]

1.50 [38.1]

++ LINE TO LINE VOLTAGE.

AND OPPOSITE

NAMEPLATE

.28 [7.1] WIDE

4 PLACES

MOUNTING SLOTS

- TT IF GANGED UNITS ARE USED IN A SYSTEM THAT ORDINARILY HAS A COMMON NEUTRAL OR GROUND BETWEEN SOURCE AND LOAD, THE NEUTRAL OR GROUND MUST BE CONNECTED TO THE COMMON TERMINALS OF THE VARIABLE TRANSFORMER ASSEMBLY. IF THE SYSTEM HAS NO NEUTRAL, THE LOAD MUST BE BALANCED OR THE TRANSFORMER WILL BE DAMAGED.
- JUMPER PROVIDED IN STANDARD COMMON POSITION AND SHOULD BE MOVED OR REMOVED AS REQUIRED.